



Socket (lamp) height adjustment options:

- Rotate threaded brass lamp rod holding socket
 - Move brass nuts on lamp rod and re-secure
 - Fine tune by bending stainless mounting strap
- Consider future lamp change - leave extra wire

LED bipin lamp shown - 12 volt standard

- Position LED just above design space for max light spread, position lamp higher to reduce glare
- Use single LED lamp for best shadow patterns

6" cast iron cap

1/4" Set Screw - use 1/8" hex key to secure cap
- Maintenance: lubricate threads at cap removal

Socket assembly mounting strap (stainless steel)
- Lubricate screws at lamp change

1/4" Philips screws with flange nuts as spacers
thread into 6x6 to secure socket mounting strap
- Long blade Philips screw driver best

6x6x13" & 6x6x19" Installation

6x6x13 inch = Beacon
6x6x19 inch = Grande Beacon
Options: Surface Mount

Lava
Lamp
Design

Attraction Lights, LLC

www.AttractionLights.com
info@attractionlights.com
970-316-0019

False bottom plate (option) covers ABS base
- Maintenance: remove debris

Corner tube routes lead wires to base
where they exit fixture corner

Lifetime Guarantee Void if fixture

metal base buried - Cover ABS base with mulch
ABS coupling fits over pipe/stake,
rotate fixture for best viewing angle
Option - glue for extra stability

Hex screws (4) secure fixture to ABS coupling

Stake Install: The top of ABS stake will be at
the bottom of the metal fixture after installed.
Therefore, stake top should be 1" above soil.

ABS 4" pipe/stake
Option - backfill with concrete for extra stability

Stake wiring hole, house wire connections in pipe