

- Socket Assembly**
- Stainless bracket with screws and flange nut
  - Supports LED Flood, also see Top Detail
  - 3 screws (1/4x20x1/2") + flange nuts, 1 washer

- LED Flood Fixture**
- UL rated wet location for 85-277 volt option
  - 10 watt, 800 lumens, 3000K, 4 yr guarantee

- Top enclosure plate welded in 6x6 top**
- LED Flood rests on plate


### 6x6x42" & 6x6x34" Bollards

- \* PLAN IS A GENERAL RECOMMENDATION ADJUST TO LOCAL ELECTRICAL CODES
- \* Attraction Lights supplies NO electrical parts except LED Flood with lead wire

Aspen Design

- 9" cap -  $\frac{3}{16}$ " steel
- 2 set screws (5/16x18x3/8") secure cap
- Use 5/32" hex key
- Anti-Tamper Feature: Not for powder coat option
- On job site, mark set screw center on blocking
- Drill 1/4" hole in blocking
- Prevents cap from being pulled off
- Wire pipe routes lead wires to base (3/8" ID)
- Note: Ventilation slots added to 6x6 top enclosure for LED Flood cooling

Top Enclosure Plate



Attraction Lights, LLC  
[www.AttractionLights.com](http://www.AttractionLights.com)  
[info@attractionlights.com](mailto:info@attractionlights.com)  
 970-316-0019

- Strain relief fitting and cover on J box**

- Lead wires from LED Flood Fixture**
- Connections in weatherproof J Box
  - J Box is free standing in 6x6 Bollard base

- Base Plate Assembly:**
- Secures and levels fixture on concrete pier
  - 3" center hole allows 2 - 1" conduit

- False bottom plate typically welded into 6x6 base
- Access opening for base wiring (one side)
- 6x6x42" & 6x6x34" Bollards only
- 4 Screws secure (Phillips 1/4x20x1/2") cover plate
- 4 set screws (5/16x18x3/8") secure bollard 6x6 body to base plate, use 5/32" hex key
- Note:** Base Plate: Slot side under access opening

**Lifetime Bollard Guarantee Void** if soil covers Bollard steel base - hide pier with mulch

"L" - 1" conduit(s) for power supply wires

- 1/2 x 8" dip galvanized anchor bolts
- Concrete Pier:** (8" diameter, depth varies)
- Also see Base Plate Detail sheet
- Hardware, template and instructions supplied